You can search for the updated part code through ITSELF web site.
URL : http://itself.sec.samsung.co.kr

7. Electrical Parts List

7-1 CS21A11ENAXXST

Level	Loc. No.	Code No.	Description ; Specification	Remark
			ASSY COVER FRONT	
1	M0001	AA90-04613F	ASSY COVER FRONT;CS21A11ENAXXST	S.N.A
..2	T0081	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
..2	T0081	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	T0081	6003-001268	SCREW-TAPTITE;TH,+,B,M4,L12,ZPC(YEL),SWR	
..2	SPK+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2	SC016	AA60-10050R	SCREW-ASSY;-,SWRCH18A,M5,L31.5,HH,+,WC,-	S.N.A
..2	T0081	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2		AA63-60004P	SPACER-GUM,CRT;-,NTR RUBBER,-,-,-,GRY,T2	S.N.A
..2		AA65-00009B	CLAMPER CORE-D,COIL;21A8,NYLON 66,V0,-,-	S.N.A
..2	T0003	AA96-01493E	ASSY COVER P-FRONT;21A11,HIPS HB,G4309,S	
...3	T0081	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
...3	T0081	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
...3	T0069	AA60-00091A	SPACER-FELT;-,FELT,150X10,-,-,BLK,T0.35,	S.N.A
...3	T0245	AA61-00711D	HOLDER-PCB;29U1,U2,HIPS VO,BK502(HB-PROP	S.N.A
...3		AA61-40113A	STOPPER-PCB;501H,HIPS,-,-,HB,NTR,-	S.N.A
...3	CIS7	AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	S.N.A
...3	T0299	AA64-03338A	WINDOW-RMC,LED;32A11,PC,CLR	
...3	T0023	AA64-03345A	KNOB-POWER;32A11,ABS,HB,G4309,SVM3012	
...3	CIS3	AA64-03431D	CABINET FRONT;21A11,HIPS,HB,G4309,SV012P	S.N.A
...3	T0022	AA64-03572A	KNOB CONTROL;21A11,ABS,HB,G4309,SVM3132	S.N.A
...3	T0578	AA64-60448W	INLAY AV;S51A,PS SHEET,T0.3,BLK,SILVER E	S.N.A
...3	T0057	AA64-70123A	BADGE-BRAND;NEW,AL,L50,FLAT,SILVER,SAMSU	S.N.A
...3		AA65-00011C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
..2	T0175	AA96-01572A	ASSY SPEAKER P;8ohm,semidome,10W,AA91-00	S.N.A
			ASSY COVER REAR	
1	M0002	AA90-04614F	ASSY COVER REAR;CS21A11ENAXXST	S.N.A
..2	T0069	AA60-00091J	SPACER-FELT;-,FELT,330X10,-,-,BLK,T0.5,-	S.N.A
..2		AA64-00892F	INLAY-BACK;D2,D3,PS SHEET,T0.3,-,-,BLK,R	S.N.A
..2	T0015	AA64-03432A	CABINET-BACK;21A11,HIPS,FV2,GR503	
..2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	S.N.A
			ASSY CPT	
1		AA91-04038A	ASSY CPT;CS21K3STX/SMA,MALAYSIA,+350MG,A	S.N.A
..2		AA91-04039A	ASSY CPT;CS21K3STX/SMA,MALAYSIA,+350MG,A	S.N.A
⚠ ...3	T0063	AA03-00333A	CRT COLOR;A51LVV896X,350MG,1.8MH,18MH,2.	
...3	T0079	AA27-00002A	MAGNET CONVERGENCE;-,JH291-SC-OB,29.1MM	
...3	T0078	AA27-00229A	DEFLECTION YOKE;-,KDY3NWE15B,S/T-3,A51LV	
...3		AA63-60028A	SPACER-DY;-,NEOPRENE,-,-,-,BLK,-,-,V0 W1	S.N.A
..2		AA98-70014D	ASSY TBC WIRE(P);-,22 Q,NTSC,PAL,1P,TVI	S.N.A
..2	T0089	AA27-00073A	COIL DEGAUSSING;-,CT201H,4.5mH,20%,48,9,	
			ASSY CHASSIS	
1	M0017	AA91-06212E	ASSY CHASSIS;,KS2A	S.N.A
..2	T0073	AA94-12299F	ASSY PCB MAIN;,KS2A	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3	T0083	0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
...3	T0083	0402-001160	DIODE-BRIDGE;D5SB60,600V,6A,SIP-4,-	

Level	Loc. No.	Code No.	Description ; Specification	Remark
...3	T0083	0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	
...3	T0090	0502-001136	TR-POWER;KSD5703,NPN,70W,TO-3PF,ST,8-	
⚠ ...3	PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
...3	IC112	1103-001171	IC-EEPROM;L51DC,16KBit,DIP,8P,300MIL,10m	
...3	T0123	1203-002085	IC-VOLTAGE REGULATOR;78R08,TO-220,4P,-,P	
...3	IC118	1204-001812	IC-VIDEO PROCESS;VDP3130Y-B2,DIP,64P,760	
⚠ ...3	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
...3	P803T	1404-001156	THERMISTOR-PTC;9OHM,+30%/-20%,220VRMS,27	
...3	C598	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,BK,15X	
...3	C407	2301-001338	C-FILM,LEAD-OTHER;0.68NF,5%,1.6KV,BK,28X	
⚠ ...3	CX802S	2306-000318	C-FILM,LEAD-PPF;220NF,20%,250V,BK,-,22.5	
⚠ ...3	CX801S	2306-000318	C-FILM,LEAD-PPF;220NF,20%,250V,BK,-,22.5	
⚠ ...3	CR402S	2306-000326	C-FILM,LEAD-PPF;4.7NF,5%,1.6KV,BK,28.5X1	
⚠ ...3	CR401S	2306-000326	C-FILM,LEAD-PPF;4.7NF,5%,1.6KV,BK,28.5X1	
⚠ ...3	CR405S	2306-000350	C-FILM,LEAD-PPF;270NF,5%,400V,BK,26X18.5	
...3	C701	2401-003031	C-AL;470uF,20%,450V,GP,BK,35x45mm,1	
...3	C701	2401-003633	C-AL;220UF,20%,160V,GP,ST,22X25MM,10	
...3	X201	2801-004019	CRYSTAL-UNIT;20.25MHz,30ppm,28-AAM,13pF,	
...3	X601	2801-004020	CRYSTAL-UNIT;18.432MHz,30ppm,28-AAM,12pF	
⚠ ...3	FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
⚠ ...3	V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
...3	CN906	3711-003043	CONNECTOR-HEADER;BOX,4P,1R,2.5MM,STRAIGH	
...3	JA701	3722-001333	JACK-PIN;9P,3.2mm,NI,BLK,-	
...3	JA702	3722-001596	JACK-PIN;3P/9P,3.5mm,NI,BLK(GRN/BLU/RED)	
⚠ ...3	T801S	AA26-00044A	TRANS SWITCHING;-,-,-,AC90~260V,DC135/15	
⚠ ...3	T401	AA26-50001M	TRANS-HORIZ.DRIVE;-,-,-,80mH,-,-,520uH,-	
...3	L808	AA27-00098A	COIL CHOKE;-,-,24uH,10%,-,0.1,3.0A,DR10X	
⚠ ...3	CR404S	AA27-00147A	COIL HORIZ. WIDTH;,170UH,BK,54T+2-2	
...3	T0296	AA27-00160A	COIL LINEARITY;64UH,64UH,L-81 OWA 12X15,	
⚠ ...3	LX801S	AA29-30002F	FILTER LINE NOISE;-,6mH,2.45A,-,-	
...3	T0245	AA39-20010H	LEAD CONNECTOR-ASSY;,1P,300,YFH800-01,S,	
...3	T0245	AA39-20053A	LEAD CONNECTOR-ASSY;,5P,400,YBNH025-05,S	
...3	T0245	AA39-20054A	LEAD CONNECTOR-ASSY;,6P,400,YBNH025-06,S	
⚠ ...3	TU01S	AA40-00082A	TUNER;TCPS3001PD16D(S),PAL-M(NTSC),181CH	
...3	GT301	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5-,NYLON66	S.N.A
...3		AA61-00707B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
...3	T0016	AA95-01854C	ASSY SUB-PCB,VIDEO S/W;29A6,KS3APAL,AA95	
....4		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
....4	IC106	1001-001114	IC-VIDEO SWITCH;TEA6425,VIDEO SWITCH ,DI	
....4	CN906	3711-002704	CONNECTOR-HEADER;NOWALL,6P,1R,2.5mm,ANGL	
....4	CN906	3711-002706	CONNECTOR-HEADER;NOWALL,8P,1R,2.5mm,ANGL	
....4		AA97-05147A	ASSY AUTO-VIDEO S/W;TXM3292,KS3A,AA41-00	S.N.A
.....5	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
.....5	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
.....5	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
.....5	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
.....5	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
.....5	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
.....5	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
.....5	C701	2401-002009	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	LS01	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
.....5	CN906	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
.....5	0	AA41-00153E	PCB-VIDEO SWITCH;CS29A6,FR-1,1L,E,1.6T,2	S.N.A
⚠ ...3	IC804	AA96-00243C	ASSY H/S;-,REGULATOR,AA62-00045A,KA7806,	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4	T0087	1203-000284	IC-POSI.FIXED REG.;7806,TO-220,3P,-,PLAS	
....4	T0081	6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-	S.N.A
...3	DDR01	AA96-00469F	ASSY H/S;-,REGULATOR,AA62-00053B,D10U60S	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4	T0083	0402-001358	DIODE-RECTIFIER;FFPF10U60S,600V,10A,TO-2	
....4	T0083	0402-001375	DIODE-RECTIFIER;FFPF10U20S,200V,10A,TO-2	
....4	T0123	1203-002018	IC-VOLTAGE REGULATOR;78R05,TO-220,4P,10M	
....4	T0081	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
....4		AA62-00053B	HEAT SINK;DREAM (D2,D3),AL ,T1.0,147,50,	S.N.A
...3	IC501	AA96-00582A	ASSY H/S;-,CRT,AA62-00096A,STV5109,KS1A	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4	T0074	1201-001687	IC-VIDEO AMP;STV5109,ZIP,15P,-,SINGLE,50	
....4	T0081	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
....4		AA62-00096A	HEAT SINK;KS2A,AL5052,T1.0,W36.0,H35.0,S	S.N.A
⚠ ...3	IC801S	AA96-50373F	ASSY H/S;-,PWM,AA62-30181K,KA3A1265RD,IC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4	T0081	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	IC063	AA13-00101A	IC HYBRID;KA3S1265RD,CN5039,5PIN,-50TO12	
....4		AA61-10386A	BRACKET-IC;100,SECC,T1.0,KA2S0680	S.N.A
....4		AA62-30181K	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,40MM,-	S.N.A
...3	IC602	AA96-50398A	ASSY H/S;-,-,AA62-30182E,TDA7297,-	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4	T0124	1201-001064	IC-POWER AMP;7297,ZIP,15P,-,DUAL,32dB,PL	
....4	T0081	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30182E	HEAT SINK-ES;-,A6063 EXTR,-,WHT,-,-,-,40	S.N.A
...3	IC301	AA96-50406G	ASSY H/S;,POWER,AA62-30180K,K57A	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	T0088	1204-001807	IC-VERTICAL PROCESSO;LA7841,SIP,7P,708MI	
....4	T0081	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	CIS	AA62-30180K	HEAT SINK-ES;-,A6063 EXTR,-,WHT,50/13,-,	S.N.A
...3		AA97-07345A	ASSY AUTO-MAIN;CS21M6GNAX/XST,KS2A,THALI	S.N.A
....4	D604	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D602	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D508	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D503	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D804	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D906	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D908	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DZ402	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D502	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D202	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D207	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D208	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D501	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D212	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D210	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D209	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	T0083	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4	T0083	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4	T0083	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4	T0083	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4	T0083	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4	T0083	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4	T0083	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
....4	T0083	0402-000537	DIODE-RECTIFIER;RH1A,600V,0.6A,DO-204AC	
....4	T0083	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
....4	T0083	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ016	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-001167	DIODE-ZENER;MTZJ30D,30V,29.02-30.51V,500	
....4	DZ016	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
....4	DZ016	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
....4	DZ016	0403-001321	DIODE-ZENER;MTZJ6.8C,6.66-7.01V,500mW,DO	
....4	DZ016	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ016	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ016	0403-001325	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	
....4	DZ016	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	DZ016	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	DZ016	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	DZ016	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4	C1Z	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	C1Z	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	C1Z	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	C1Z	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	C1Z	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	C1Z	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	C1Z	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	C1Z	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	T0156	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	T0156	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	T0156	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0090	0502-001007	TR-POWER;KSC2073-H2,NPN,25W,TO-220,ST,6	
....4	IC012	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
....4	IC904	1203-001943	IC-VOL. DETECTOR;7025,TO-92,3P,-,PLASTIC	
....4	T0087	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
⚠ 4	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
⚠ 4	VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
....4	R125	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4	R125	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4	R125	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4	R125	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4	R125	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R075	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4	R075	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-000117	R-CARBON(S);68OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R125	2001-000214	R-CARBON;1.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000214	R-CARBON;1.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000232	R-CARBON;1.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	R125	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100O

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	R075	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R075	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-001165	R-CARBON(S);56OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-001187	R-CARBON(S);75OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-001410	R-CARBON(S);43OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R518	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
....4	R515	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
....4	R512	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
....4	R521	2002-001009	R-COMPOSITION;2.7Kohm,10%,1/2W,AA,TP,3.7	
⚠ 4	RP801S	2002-001010	R-COMPOSITION;1.8Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	RY801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	RY802S	2002-001013	R-COMPOSITION;4.7Mohm,5%,1/2W,AA,TP,3.7x	
....4	R426	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
....4	R434	2003-000664	R-METAL OXIDE(S);33ohm,5%,2W,AF,TP,4x12m	
....4	R807	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	R808	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	R804	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
....4	R803	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
....4	R802	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
....4	R403	2003-002037	R-METAL OXIDE(S);270ohm,5%,2W,AF,TP,3.9x	
....4	R436	2003-002151	R-METAL OXIDE;18KOHM,5%,2W,AG,TP,6X16MM	
....4	R305	2003-002182	R-METAL OXIDE(S);470ohm,5%,2W,AG,TP,3.9x	
....4	R306	2003-002182	R-METAL OXIDE(S);470ohm,5%,2W,AG,TP,3.9x	
....4	R402	2003-002186	R-METAL OXIDE(S);22Kohm,5%,2W,AG,TP,3.9x	
....4	R401	2003-002186	R-METAL OXIDE(S);22Kohm,5%,2W,AG,TP,3.9x	
....4	R835	2003-002211	R-METAL OXIDE(S);91Kohm,5%,2W,AG,TP,3.9x	
....4	R836	2003-002211	R-METAL OXIDE(S);91Kohm,5%,2W,AG,TP,3.9x	
....4	R212	2004-000218	R-METAL;10Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
....4	R313	2004-001137	R-METAL;6.8Kohm,1%,1/8W,AA,TP,1.8x3.2m	
....4	R024	2004-001377	R-METAL(S);120Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R024	2004-001397	R-METAL(S);4.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R024	2004-001397	R-METAL(S);4.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R024	2004-001397	R-METAL(S);4.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R024	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
....4	R024	2004-001986	R-METAL(S);35.7Kohm,1%,1/2W,AA,TP,2.4x6.	
....4	R024	2004-004970	R-METAL(S);62Kohm,1%,1/8W,AA,TP,1.8x3.2m	
....4	R024	2004-005020	R-METAL(S);27.5KOHM,1%,1/2W,AA,TP,2.5X6.	
....4	R522	2008-000206	R-FUSIBLE(S);1ohm,5%,1/2W,AF,TP,2.5x6.5m	
....4	R523	2008-000251	R-FUSIBLE(S);0.27ohm,5%,2W,AF,TP,3.9x10m	
....4	R828	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
....4	R829	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
....4	R827	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
....4	R405	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
....4	R433	2008-001127	R-FUSIBLE(S);6.8Kohm,5%,1W,AF,TP,3.9X10m	
....4	R304	2008-001140	R-FUSIBLE(S);0.9OHM,5%,2W,AF,TP,3.9X10MM	
....4	C598	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
....4	C598	2201-000193	C-CERAMIC,DISC;0.01NF,0.25PF,50V,C0G,TP,	
....4	C598	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
....4	C598	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
....4	C598	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
....4	C598	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
....4	C598	2201-000504	C-CERAMIC,DISC;0.039NF,5%,50V,SL,TP,5X3M	
....4	C598	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000558	C-CERAMIC,DISC;0.47NF,10%,50V,Y5P,TP,5X3	
....4	C598	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000681	C-CERAMIC,DISC;0.082NF,5%,50V,SL,TP,5X3M	
....4	C598	2201-000723	C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X5	
....4	C598	2201-000980	C-CERAMIC,DISC;0.03NF,5%,50V,C0G,TP,5X3M	
....4	C598	2201-000980	C-CERAMIC,DISC;0.03NF,5%,50V,C0G,TP,5X3M	
....4	C598	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
....4	C598	2201-002031	C-CERAMIC,DISC;0.005NF,0.5PF,50V,C0G,TP,	
....4	C598	2201-002031	C-CERAMIC,DISC;0.005NF,0.5PF,50V,C0G,TP,	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000205	C-CERAMIC,MLC-AXIAL;22pF,5%,50V,SL,TP,1.	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	C689	2202-000205	C-CERAMIC,MLC-AXIAL;22pF,5%,50V,SL,TP,1.	
....4	C689	2202-000205	C-CERAMIC,MLC-AXIAL;22pF,5%,50V,SL,TP,1.	
....4	C689	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C689	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C689	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C689	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C689	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4	C689	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
....4	C689	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000863	C-CERAMIC,MLC-AXIAL;560pF,10%,50V,Y5P,TP	
....4	C689	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C689	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C689	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C689	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C689	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C689	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C689	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C689	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C689	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C689	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
....4	C2560	2301-000192	C-FILM,LEAD-PEF;1nF,5%,50V,TP,5.3x10mm,5	
....4	C2560	2301-000254	C-FILM,LEAD-PEF;39nF,5%,50V,TP,7.5x3.5x6	
....4	C2560	2301-000310	C-FILM,LEAD-PEF;68nF,5%,50V,TP,8.0X8.5X4	
....4	C2560	2301-000310	C-FILM,LEAD-PEF;68nF,5%,50V,TP,8.0X8.5X4	
....4	C2560	2301-000314	C-FILM,LEAD-PEF;8.2nF,5%,50V,TP,6.5x3.0x	
....4	C2560	2301-000314	C-FILM,LEAD-PEF;8.2nF,5%,50V,TP,6.5x3.0x	
....4	C2560	2301-000342	C-FILM,LEAD-PEF;2.2nF,5%,50V,TP,7.4x3.9x	
....4	C2560	2301-000356	C-FILM,LEAD-PEF;47nF,5%,50V,TP,7.5x4.0x6	
....4	C2560	2301-000356	C-FILM,LEAD-PEF;47nF,5%,50V,TP,7.5x4.0x6	
....4	C2560	2301-000356	C-FILM,LEAD-PEF;47nF,5%,50V,TP,7.5x4.0x6	
....4	C2560	2301-000383	C-FILM,LEAD-PEF;10nF,5%,50V,TP,6x7x3.2mm	
....4	C2560	2301-000383	C-FILM,LEAD-PEF;10nF,5%,50V,TP,6x7x3.2mm	
⚠ 4	C420	2301-001065	C-FILM,LEAD-PPF;47nF,5%,630V,TP,19x15.5x	
....4	CR403S	2301-001067	C-FILM,LEAD-PPF;82nF,5%,400V,TP,19x15.5x	
....4	C807	2301-001435	C-FILM,LEAD-PPF;1.5nF,5%,1.2kV,TP,15x8x1	
....4	C2560	2305-000149	C-FILM,LEAD-PEF;100nF,5%,100V,TP,12x12.5	
....4	C2560	2305-000285	C-FILM,LEAD-PEF;220NF,5%,100V,TP,10.5X5.	
....4	C2560	2305-000382	C-FILM,LEAD-PEF;4.7nF,5%,400V,TP,-,5mm	
....4	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000704	C-FILM,LEAD-PEF;100nF,5%,250V,TP,16.5x10	
....4	C2560	2305-000704	C-FILM,LEAD-PEF;100nF,5%,250V,TP,16.5x10	
....4	C701	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-000142	C-AL;1000uF,20%,16V,WT,TP,10x20,5	
....4	C701	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
....4	C701	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	C701	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
....4	C701	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
....4	C701	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
....4	C701	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
....4	C701	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
....4	C701	2401-000603	C-AL;1UF,20%,50V,GP,TP,5X11,2	
....4	C701	2401-000603	C-AL;1UF,20%,50V,GP,TP,5X11,2	
....4	C701	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
....4	C701	2401-000711	C-AL;2200uF,20%,25V,GP,TP,16x25,7.5	
....4	C701	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	C701	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
....4	C701	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
....4	C701	2401-001054	C-AL;3300uF,20%,25V,GP,TP,18x25,7.5	
....4	C701	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5	
....4	C701	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
....4	C701	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
....4	C701	2401-001527	C-AL;47uF,20%,250V,HR,TP,13x25mm,5m	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-001914	C-AL;1uF,20%,50V,BP,TP,5x11,5	
....4	C701	2401-001914	C-AL;1uF,20%,50V,BP,TP,5x11,5	
....4	C701	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
....4	C701	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
....4	C701	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
....4	C701	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C701	2401-002267	C-AL;2.2uF,20%,250V,GP,TP,8x11.5,5	
....4	C701	2401-002267	C-AL;2.2uF,20%,250V,GP,TP,8x11.5,5	
....4	C701	2401-002300	C-AL;47uF,20%,50V,GP,TP,6.3x11,5	
....4	C701	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	C701	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	C701	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	C701	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
....4	C701	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
....4	C701	2401-003139	C-AL;1000uF,20%,25V,WT,TP,10*20,5mm	
....4	C701	2401-003561	C-AL;1uF,10%,50V,GP,TP,5x11mm,5	
....4	C701	2401-003561	C-AL;1uF,10%,50V,GP,TP,5x11mm,5	
....4	C701	2401-003561	C-AL;1uF,10%,50V,GP,TP,5x11mm,5	
....4	CW901	2503-000156	C-NETWORK;100pFx4,20%,50V	
....4	R605	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	R604	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	L907	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	L906	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	L202	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	L301	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	L602	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	L603	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	L103	2701-000115	INDUCTOR-AXIAL;10uH,10%,3070	
....4	L205	2701-000142	INDUCTOR-AXIAL;1uH,10%,2534	
....4	J707	2701-000142	INDUCTOR-AXIAL;1uH,10%,2534	
....4	J706	2701-000142	INDUCTOR-AXIAL;1uH,10%,2534	
....4	J705	2701-000142	INDUCTOR-AXIAL;1uH,10%,2534	
....4	L604	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2534	
....4	L209	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2534	
....4	L208	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2534	
....4	L207	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2534	
....4	J699	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2534	
....4	L706	2701-000177	INDUCTOR-AXIAL;33uH,10%,2534	
....4	L705	2701-000177	INDUCTOR-AXIAL;33uH,10%,2534	
....4	L608	2701-000177	INDUCTOR-AXIAL;33uH,10%,2534	
....4	L607	2701-000177	INDUCTOR-AXIAL;33uH,10%,2534	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	J920	2701-000177	INDUCTOR-AXIAL;33uH,10%,2534	
....4	L902	2701-000183	INDUCTOR-AXIAL;39uH,5%,2534	
....4	L904	2702-001094	INDUCTOR-RADIAL;10uH,10%,4x6mm	
....4	L903	2702-001094	INDUCTOR-RADIAL;10uH,10%,4x6mm	
....4	L901	2702-001094	INDUCTOR-RADIAL;10uH,10%,4x6mm	
....4	L609	2702-001094	INDUCTOR-RADIAL;10uH,10%,4x6mm	
....4	L601	2702-001094	INDUCTOR-RADIAL;10uH,10%,4x6mm	
....4	L204	2702-001094	INDUCTOR-RADIAL;10uH,10%,4x6mm	
....4	L201	2702-001094	INDUCTOR-RADIAL;10uH,10%,4x6mm	
....4	R519	2702-001096	INDUCTOR-RADIAL;33uH,10%,4x6mm	
....4	X901	2801-003728	CRYSTAL-UNIT;6MHz,30ppm,28-AAM,20pF,40oh	
....4	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L802	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	L803	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	L806	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	L809	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	L302	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	L303	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	L610	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	L801	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
⚠ 4	FD803S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
⚠ 4	FD801S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
⚠ 4	FD802S	3601-001228	FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	
....4	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
....4	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
....4	CN906	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
....4	CN906	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
....4	CN906	3711-002647	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH	
....4	EY830	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY828	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY827	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY826	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY825	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY824	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY823	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY831	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY838	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY837	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY836	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY835	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY834	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY833	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY832	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY814	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY813	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY812	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY811	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY810	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY809	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY808	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY815	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY821	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY819	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY817	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY816	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY861	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY860	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY859	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY858	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY856	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY855	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY854	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY871	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY870	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY867	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY866	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY865	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY864	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY863	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY845	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY844	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY842	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY841	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY839	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	EY846	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY853	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY852	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY851	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY850	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY849	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY848	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY847	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY807	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY419	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY418	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY417	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY416	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY415	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY414	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY421	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY426	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY425	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY424	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY423	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY422	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY402	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY401	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY303	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY301	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EL801	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY403	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY413	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY412	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY411	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY410	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY409	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY406	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY405	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY606	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY605	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY604	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY603	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY602	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY601	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY445	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY701	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY806	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY805	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY804	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY803	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY802	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY801	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY702	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY435	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY434	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY433	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY432	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY431	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY430	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY429	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY436	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY441	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY440	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY437	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY438	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY439	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL803	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL805	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL806	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL807	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL808	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL401	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL402	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL405	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL404	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT503	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT101	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT102	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT407	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	C2560	2301-000148	C-FILM,LEAD-PEF;10nF,5%,100V,TP,7x3.2x7m	
....4	R424	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
....4	R425	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
....4	R227	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
....4	PCB	AA41-00132K	PCB-MAIN;CS2139T,FR-1,1L,K,1.6T,330X245,	S.N.A
....4	C689	2202-000719	C-CERAMIC,MLC-AXIAL;6.8nF,20%,16V,Y5R,TP	
....4	L102	2701-001090	INDUCTOR-AXIAL;0.56uH,10%,3070	
....4	C701	2401-003102	C-AL;100uF,20%,10V,GP,TP,5x11,5	
....4	C701	2401-003036	C-AL;100uF,20%,16V,GP,TP,5X11mm,5mm	
⚠ ...3	T444S	AA26-00205A	TRANS FBT;FFA61012L,CPTTV,3.4mH,FERRITE,	
...3	T0204	AA95-03155A	ASSY SUB PCB-PIP;,KS2A,PAL,1T-PIP,SDA948	
....4		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
....4		0202-001167	SOLDER-CREAM;RX3603-2330HO,S45A,PASTE,SN	S.N.A
....4	CN906	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
....4	CN906	3711-002706	CONNECTOR-HEADER;NOWALL,8P,1R,2.5mm,ANGL	
....4	CN906	3711-002709	CONNECTOR-HEADER;NOWALL,12P,1R,2.5mm,ANG	
....4	HCP01	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4		AA97-13774A	ASSY AUTO-PIP;,KS2A,PAL-1T-PIP,SDA9488X-	S.N.A
.....5	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
.....5	C701	2401-000603	C-AL;1UF,20%,50V,GP,TP,5X11,2	
.....5	C701	2401-000667	C-AL;2.2uF,20%,50V,WT,TP,5x11,5	
.....5	C701	2401-000667	C-AL;2.2uF,20%,50V,WT,TP,5x11,5	
.....5		AA97-13776A	ASSY SMD-PIP;,KS2A,PAL, 1T-PIP,SDA9488X-	S.N.A
.....6	DP04	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DP03	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DP02	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DP01	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....6	DZ016	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
.....6	DZ016	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
.....6	DZ016	0403-001127	DIODE-ZENER;02DZ5.1,5.1,200mW,SOD-323,TP	
.....6	T0156	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	T0156	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	T0156	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6	T0156	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	T0156	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	T0156	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	T0156	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6	T0087	1203-001359	IC-POSI.FIXED REG.;1086,TO-263,3P,15.8MM	
.....6	ICP01	1204-002100	IC-PICTURE PROCESS;SDA9488X-B31,SOIC,28P	
.....6	RP43	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
.....6	RP42	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
.....6	RP41	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
.....6	RP40	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
.....6	RP14	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
.....6	RP13	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
.....6	RP12	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
.....6	RP02	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
.....6	RP01	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
.....6	RP32	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
.....6	RP33	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
.....6	RP34	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
.....6	RP35	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
.....6	RP36	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
.....6	RP03	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
.....6	RP04	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
.....6	RP05	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
.....6	RP07	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
.....6	RP31	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
.....6	RP22	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
.....6	RP21	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
.....6	RP06	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
.....6	RP30	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
.....6	RP29	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
.....6	RP26	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....6	RP25	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
.....6	RP28	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608	
.....6	RP27	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608	
.....6	RP24	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608	
.....6	RP23	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608	
.....6	RP50	2007-000121	R-CHIP;820ohm,5%,1/10W,TP,1608	
.....6	RP15	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
.....6	T0657	2203-000181	C-CER,CHIP;100nF,+80-20%,25V,Y5V,TP,2012	
.....6	T0657	2203-000181	C-CER,CHIP;100nF,+80-20%,25V,Y5V,TP,2012	
.....6	T0657	2203-000181	C-CER,CHIP;100nF,+80-20%,25V,Y5V,TP,2012	
.....6	T0657	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	T0657	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	T0657	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	T0657	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	T0657	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	T0657	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	T0657	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	T0657	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
.....6	T0657	2203-000384	C-CER,CHIP;0.015NF,5%,50V,C0G,TP,1608	
.....6	T0657	2203-000384	C-CER,CHIP;0.015NF,5%,50V,C0G,TP,1608	
.....6	T0657	2203-005030	C-CER,CHIP;470nF,+80-20%,50V,Y5V,TP,3216	
.....6	T0657	2203-005030	C-CER,CHIP;470nF,+80-20%,50V,Y5V,TP,3216	
.....6	T0052	2703-000392	INDUCTOR-SMD;10uH,5%,4532	
.....6	T0052	2703-000392	INDUCTOR-SMD;10uH,5%,4532	
.....6	PCB	AA41-00466B	PCB-PIP;CS29A6PF8X,CEM-3,2L,A,1.6T,180X2	S.N.A
....4	XP01	2801-004019	CRYSTAL-UNIT;20.25MHz,30ppm,28-AAM,13pF,	
...3	M0018	AA97-06805C	ASSY MICOM;,KS3A,SDA555X,SIM806EA3,02111	
....4	T0119	AA09-00041A	IC MICOM;,SDA555X-OTP,3.3V,-,128K,SDIP,-	S.N.A
...3	IC601	1204-002038	IC-SOUND PROCESSOR;MSP3410G-PO-83V3,PSDI	
..2	T0098	AA94-12683A	ASSY PCB MISC-CONTROL;,K55A	
...3	LDY01	0601-001381	LED;ROUND,RED/GRN,5.0MM,650/563NM	
...3	RMY01	AA32-00012A	MODULE REMOCON;ORC-50HF2,38KHZ,940NM,MES	
...3	T0245	AA39-00100B	LEAD CONNECTOR-ASSY;,4P,400MM,YBNH250-04	
...3	T0245	AA39-20069C	LEAD CONNECTOR-ASSY;,5P,400,YBNH025-05,6	
...3		AA97-13797A	ASSY AUTO;,K55A	S.N.A
....4	DY02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DY01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	R125	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R075	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R125	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-002291	C-AL;47uF,20%,16V,GP,TP,6.3x5,5	
....4	LY01	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	M0119	AA41-00898B	PCB CONTROL;WS28A11,FR-1,1L,B,1.6T,203*4	S.N.A
....4	SWY07	3404-000243	SWITCH-TACT;15V,20mA,160gf+-50gf,6x3.4mm	
....4	SWY08	3404-000243	SWITCH-TACT;15V,20mA,160gf+-50gf,6x3.4mm	
....4	SWY09	3404-000243	SWITCH-TACT;15V,20mA,160gf+-50gf,6x3.4mm	
....4	SWY10	3404-000243	SWITCH-TACT;15V,20mA,160gf+-50gf,6x3.4mm	
....4	SWY11	3404-000243	SWITCH-TACT;15V,20mA,160gf+-50gf,6x3.4mm	
....4	SWY12	3404-000243	SWITCH-TACT;15V,20mA,160gf+-50gf,6x3.4mm	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2	T0091	AA95-01788P	ASSY SUB-PCB,A/V SIDE;CL21M5WKX/RCL,K57A	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3	JE01	3722-000143	JACK-PHONE;1P(VER),3.4PI,AG,BLK,NO	
...3	JA01	3722-001031	JACK-PIN;3P,3.6mm,#18,AU	
...3	T0245	AA39-00070A	LEAD CONNECTOR-ASSY;,4P,200MM,YBNH250-04	
...3	T0245	AA39-20068E	LEAD CONNECTOR-ASSY;,8P,500,YBNH025-08,6	
...3	T0245	AA39-20069C	LEAD CONNECTOR-ASSY;,5P,400,YBNH025-05,6	
...3		AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A
...3		AA97-05004A	ASSY AUTO-SUB;CS29D4,S51A,PAL,11P,SIDE	S.N.A
....4	R075	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	PCB	AA41-11017D	PCB-A/V SIDE;CT-29U1,FR-1,1L,D,1.6T,245X	S.N.A
..2	T0569	AA94-12841A	ASSY PCB MISC-MASTER;,K55A	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
⚠ ...3	SW811S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
...3	CN906	3711-004696	CONNECTOR-HEADER;NOWALL,3P,1R,5MM,ANGLE,	
...3	CN906	3711-004697	CONNECTOR-HEADER;NOWALL,3P,1R,5MM,ANGLE,	
...3		AA61-00719B	HOLDER-MASTER;T6,W3,HIPS V0,BLK,J52A	S.N.A
...3		AA97-13885A	ASSY AUTO-MASTER;,K55A	S.N.A
....4	EY04	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY03	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY02	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY01	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	0	AA41-00879A	PCB-MASTER S/W;WS32Z10,CEM-1,1L,A,1.6T,S	S.N.A
...3	T0081	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
...3	T0081	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
...3	T0245	AA39-20179A	LEAD CONNECTOR-ASSY;,3(2)P,300MM,YFH800-	

ASSY FIXING

1		AA91-06400F	ASSY FIXING;,KS2A	S.N.A
..2	T0245	AA39-20010B	LEAD CONNECTOR-ASSY;,1P,500,YFH800-01,S,	
..2		AA65-30009A	CLAMPER CORE-FBT;-,ABS,V0,-,BLK,-	S.N.A
..2		AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-,	S.N.A
..2	FBT	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-,	S.N.A
..2		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
..2		AA65-30110A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
⚠ ..2	T0066	AA96-20112A	ASSY POWER CORD;-,EP2/NO,H/C300,KJ10,THA	
...3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
...3	T0077	AA39-10006K	CBF POWER CORD;-,KJ-10,SPT-2 2/18AWG,240	
...3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A

ASSY ACCESSORY

1	M0017	AA92-05261A	ASSY ACCESSORY;CS21M6GNAX/XST,THAILAND,K	S.N.A
..2	T0080	AA26-90002A	TRANS MATCHING;-,75-300ohm,PAL,40-890MHZ	
..2	T0075	AA42-00003A	ANT ROD;-,3S,720mm,ABS,UL/CSA,-	
..2	T0074	AA59-00128J	REMOCON;,TM58,DREAM-D3,34,L/GRAY,NON-TTX	
..2	M0432	AA68-00965A	MANUAL-S/D;-,-,ENG,-,W/P100G,ALL1,-,A4,-	S.N.A
..2		AA68-01068B	CARD WARRANTY;-,TSE,W/P120G,-,217*93mm,2	S.N.A
..2	T0563	AA68-01179A	MANUAL USERS;-,-,ENG,-,W/P100G,ALL1,-,B5	S.N.A
..2	T0563	AA68-01398A	MANUAL USERS;,THI.,W/P100G,ALL1,B5,KS2A,	S.N.A
..2		6902-000009	BAG PE;HDPE,T0.03,L400,W240,TRP,8,2,PE M	S.N.A

ASSY P/MATERIAL

1		AA92-07773A	ASSY P/MATERIAL;CS21A11MHPXBWT	S.N.A
..2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A
..2		6902-000061	BAG AIR;LDPE,T0.2,L1000,W500,TRP,,,	S.N.A
..2		6902-000001	BAG AIR;LDPE,T0.2,L1800,W1000,TRP,,,LDPE	S.N.A
..2		6902-000005	BAG PE;HDPE/NITRON/HDPE,T0.015/T0.5/T0.0	S.N.A

MEMO